

The 30WK wall mounting kit allows the installer to mount the Lowell MA30 mixer/amplifier to any flat wall surface such as a telephone closet termination board.

Step 1

The 30WK wall mounting kit includes two (2) brackets, two (2) 8-32 self-tapping screws, and four (4) 6-32 self-tapping screws as shown in figure **1**.

Step 2

Remove the two (2) chassis cover screws as shown in figure **2**. Also remove the same two (2) cover screws on the opposite side of the chassis.

Screw Note:

The chassis screws that you removed, have a unique metric size and thread pitch. Discard those screws. Provided with the kit are 8-32 self-tapping and 6-32 self-tapping screws that will use the existing metric threaded holes as starter holes and will thread new tapped holes that will securely attach the mounting brackets.

Step 3

Line up a bracket with the holes in the MA30 and securely tighten the one (1) 8-32 self-tapping screw and the two (2) 6-32 self-tapping screws where shown in figure **3**. Line up the second bracket with the holes on the opposite side of the MA30 and securely tighten the one (1) 8-32 self-tapping screw and two (2) 6-32 self-tapping screws. The completed assembly with both brackets installed is shown in figure **4**.

Step 4

Hold the amplifier with mounting brackets attached against the wall or surface where you want to mount the amplifier. Note that the knobs can be positioned up, down, or to either side as desired. Mark the slotted holes on the surface. Partially screw four (4) mounting bolts (provided by the installer – a screw with a 3/8" diameter head will work best) into the surface where you have marked the slot leaving the head about 1/4" off of the surface. The amplifier and brackets will now simply slip right over the screws and the screw heads will rest in the slots. Finally, tighten the four (4) mounting screws.

